





Terminal Blocks & The Others

■ HY-256/306/606/606N Power buzzer

■ Specification



Model	HY-256	HY-306	HY-606	HY-606N
Appearance				
Voltage	110 V, 220 V a.c./d.c. 12 V, 24 V d.c.			
Power consumption	4 VA : HY-256-1, HY-256-2, HY-306-1, HY-306-2 30 mA : HY-256-12, HY-256-24, HY-306-12, HY-306-24		8 VA : HY-606-1, HY-606N-1, HY-606-2, HY-606N-2 30 mA : HY-606-12, HY-606N-2, HY-606-24, HY-606N-24	
Cycle	50 / 60 Hz			
Volume(distance 1m)	85 dB			
External diameter	Ø 25	Ø 30	Ø 65	Exposure type

■ Suffix code

Model	Code	Information
HY-	<input type="checkbox"/> <input type="checkbox"/>	Power Buzzer
Dimension	256	For Ø25
	306	For Ø30
	606	Rectangular panel flush type (For Ø66)
	606N	Rectangular panel extended type (□80)
Voltage	1	110 V a.c., 50/60 Hz
	2	220 V a.c., 50/60 Hz
	12	12 d.c.
	24	24 d.c.

■ HY-606MD/MA 4 tones melody buzzer

■ Specification



Model	HY-606MD	HY-606MA
Appearance		
Voltage	12 / 24 V d.c.	110 / 220 V a.c.
Power consumption	2.5 W	
Frequency	—	50 / 60 Hz
Volume (distance 1m)	98 dB max	
Diameter	Ø 66	

■ Suffix code

Model	Code	Information
HY-606	<input type="checkbox"/>	4 tones melody buzzer
Dimension	MD	12 / 24 V d.c.
	MA	110 / 240 V a.c.

■ HY-226M/256M 3 tones electronic buzzer

■ Specification

Model	HY-226MD,MA	HY-256MD,MA
Appearance		
Voltage	100 – 240 V a.c./ 12, 24 V d.c.	
Power consumption	0.6 W / 13.5 W	
Frequency	50/60 Hz	
Volume(distance 1m)	80 dB	
Diameter	Ø 22/Ø 25	Ø 25

■ Suffix code

Model	Code	Information
HY-	<input type="checkbox"/> <input type="checkbox"/>	3 tones electronic buzzer
Dimension	226	Ø22 / Ø25 dual usage (Front side : rectangular type)
	256	For Ø25 installation (Front side : round type)
Voltage	MD	12 – 24 V d.c./a.c.
	MA	100 – 240 V a.c.